


### Kura X1


IP65 IK 06 1J xx3 CE UK ER	LED		REAL LM	COL.	CODE *
	W	LM			
	3	180	150	☐ ✓ 220-240 V	○ LL14701W
					● LL14701B
	2	180	150	◇ ⊗ 700mA-3V	○ LZ14701W
					● LZ14701B



\* Complete the CODE    ○ OPTIC   S | 18°   M | 28°   L | 52°   E | 11 X 37°   ☐ LED COLOUR   N | 4000K   3 | 3000K   2 | 2700K

### Kura X3


IP65 IK 06 1J xx3 CE UK ER	LED		REAL LM	COL.	CODE *
	W	LM			
	7,5	540	510	☐ ✓ 220-240 V	○ LL14702W
					● LL14702B
	6	540	510	◇ ⊗ 700mA-9V	○ LZ14702W
					● LZ14702B



\* Complete the CODE    ○ OPTIC   S | 18°   M | 28°   L | 52°   E | 11 X 37°   ☐ LED COLOUR   N | 4000K   3 | 3000K   2 | 2700K

### Kura X5

IP65 IK 06 1J xx3 CE UK ER	LED		REAL LM	COL.	CODE *
	W	LM			
	12,5	900	840	☐ ✓ 220-240 V	○ LL14703W
					● LL14703B
	10	900	840	◇ ⊗ 700mA-15V	○ LZ14703W
					● LZ14703B



\* Complete the CODE    ○ OPTIC   S | 18°   M | 28°   L | 52°   E | 11 X 37°   ☐ LED COLOUR   N | 4000K   3 | 3000K   2 | 2700K